



***Toll Free 800- 964-7070***

*Fax 248-623-4911*

*5492 Dixie Hwy.*

*Waterford, MI 48329*

5W 30 SYNTHETIC OIL RECOMMENDED

**How to fill your oil:**

1. Switch the breaker in the generator to off. Marked 30-100 on it. Located on the side of the generator or inside depending on the model.
2. Switch the generator Auto/Off/Manual switch to Off. This is located inside the generator on the control panel.
3. If the generator was running let it sit for about a minute before you check the oil.
4. Pull the dip stick out and see where the oil is on it. It should be towards the upper line located at the bottom of the stick.
5. If it is towards the bottom you will need to add about a quart. Add it slowly, put about half in and see where it is on the stick. **Very important** not to overfill!
6. Fill the oil through the oil fill cap.
7. Once you have filled it to the upper mark you are fine. A generator typically never needs more than a quart.
8. Once it is full, switch the Auto/Off/Manual switch back to Auto.
9. If the generator was running when you shut it down, wait about 30 seconds before you switch the breaker back on. This will give the generator a second to warm up while running, before it takes the load from the house power.
10. You are all done.